



LAWRENCE
LIVERMORE
NATIONAL
LABORATORY

Model-Based Algorithms for Detecting Cable Damage from Time-Domain Reflectometry Measurements

G. A. Clark, E. F. Breitfeller

November 15, 2005

Signal and Imaging Sciences Workshop
Livermore, CA, United States
November 17, 2005 through November 18, 2005

Disclaimer

This document was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor the University of California nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or the University of California, and shall not be used for advertising or product endorsement purposes.



MODEL-BASED ALGORITHMS FOR DETECTING CABLE DAMAGE FROM TIME-DOMAIN REFLECTOMETRY MEASUREMENTS

Grace A. Clark

EE/EETD, Systems and Decision Sciences Section

Eric F. Breitfeller

EE/DSED Signal/Image Processing and Control Group

November 17-18, 2005

This work was performed under the auspices of the U.S. Department of Energy by the University of California, Lawrence Livermore National Laboratory under Contract No. W-7405-Eng-48.

Disclaimer and Auspices Statements



This document was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor the University of California nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or the University of California, and shall not be used for advertising or product endorsement purposes.

This work was performed under the auspices of the U.S. Department of Energy by University of California, Lawrence Livermore National Laboratory under Contract W-7405-Eng-48.

We Have an Interdisciplinary Team



- **Graham Thomas - ME/MMED, NDE Group Leader for Ultrasonics/Acoustics**
 - NDE, materials characterization
 - Project Management
- **Grace Clark - EE/EETD**
 - Image/signal processing, automatic target/pattern recognition (ATR), sensor data fusion, NDE
- **Chris Robbins - EE/DSED**
 - Data acquisition, hardware
- **Eric Breidfeller - EE/DSED**
 - Signal processing, software
- **Rex Morey - EE/DSED (Retired)**
 - Time Domain Reflectometry

Agenda




- Introduction and Problem Definition - *Work in Progress*
- Technical Approach
- Model-Based Flaw Detection Results
- Discussion


We Are Testing Two-Conductor Flat Cables With Kapton Insulation




*Two-Conductor Flat Cable
With Kapton Insulation*



*Foil Simulating a Capacitive
Discontinuity (Damage)*




Red TDR Signal => Good Cable
Black TDR Signal => Damaged Cable



Benchtop Experiments (w/No Device “Mockup):” Connections Create Some Variability

Grace Clark



Capacitive Coupling & Impedance Matching:

- PIU = Half of “The Capacitor”
- Cable = Half of “The Capacitor”

Proposed Decision-Making Protocol (Using TDR Measurements):



Use a Three-Step Hierarchical Decision Scheme:

1. Detection:

- *Decide whether or not an abnormality in the cable TDR response exists (yes or no)*
- *Assume that an abnormal TDR response implies a flaw in the cable*

2. Flaw or Failure Mode Classification:

- *Classify the type of failure mode or flaw detected, from among a fixed set of possible modes*

3. Final Decision:

- *Using all of the information from the measurements and the previous two steps (fusion), decide whether the cable is “reliable or not reliable”*

Model-Based Detection:

Detect a Model Mismatch if a Flaw is Present




- Exploit the fact that the TDR measurements are reasonably repeatable.
- Build a forward model of the dynamic system (cable) for the case in which **NO FLAW** exists
- Whiteness Testing on the *Innovations (Errors)*:
Estimate the output of the actual system using measurements from a dynamic test.
 - If **no flaw** exists, the model will match the measurements, so the “innovations” (errors) will be **statistically white**.
 - If a **flaw** exists, the model will not match the measurements, so the “innovations” (errors) will **not be statistically white**.
- Weighted Sum Square Residuals (WSSR) Test:
The WSSR provides a single metric for the model mismatch

Let Us Define a “White Noise” Sequence $x(t)$




Given a stochastic process $x(t)$



$x(t)$ is “white” when:

Autocorrelation
(Time Domain)



$$\begin{aligned} R_{xx}(\tau) &= E\{x(t)x(t+\tau)\} \\ &= \delta(\tau) \\ &= \begin{cases} 1, & \tau = 0 \\ 0, & \tau \neq 0 \end{cases} \end{aligned}$$



Power Spectral Density
(Frequency Domain)


$$\begin{aligned} S_{xx}(f) &= F\{R_{xx}(\tau)\} \\ &= 1 \end{aligned}$$

$F\{\bullet\}$ = Fourier Transform




Experiment Using Real Cable TDR Signals: Raw Measurements

Grace Clark




Step #1: System Identification to Estimate the System Model of the *Unflawed Cable*

Grace Clark




$s(n)$ = *Reference Signal* (Front Reflection) From a “Long” Cable




Unflawed Case:

$x_U(n)$ = **Unflawed** Cable Output




Unflawed Case:

$\hat{x}_U(n)$ = *Estimated Unflawed Cable Output*



Unflawed Case: Residual (or “Innovations”)




Unflawed Case: Whiteness Test on the Innovations

Grace Clark



$$e_u(n) = x_u(n) - \hat{x}_u(n) = \text{Innovations}$$



The normalized auto-covariance $\hat{\rho}_e(i, k)$ of the innovations lies within the statistical confidence interval bounds (blue)

⇒ Declare that the Innovations are “White”

⇒ There is no model mismatch


⇒ ***The model is valid***

Unflawed Case: WSSR Test for the Unflawed Case

Grace Clark



$$\rho(l) = \sum_{k=l-N+1}^l \underline{e}^T(k) R_e^{-1}(k) \underline{e}(k) \quad \text{for } l \geq N \text{ (scalar)}$$



WSSR = Weighted Sum Squared Residuals


The WSSR falls within the statistical bound (blue).

⇒ There exists no model mismatch

⇒ *The unflawed model is **Valid***

Step #2: Compare the Responses of the Unflawed and Flawed Cables ==> *Flaw Detection*


Grace Clark



Flaw Detection:


- **Given:** $s(n)$ and $\hat{h}_u(n)$
- **Detect flaws by testing the innovations (nonstationary) for whiteness using WSSR (Weighted Sum Squared Residuals) over a moving window**

$s(n)$ = *Reference Signal* (Front Reflection) From a “Long” Cable



Flawed Case:


$x_F(n)$ = **Flawed** Cable Output



Flawed Case: Residual (or “Innovations”)



$$e_F(n) = x_F(n) - \hat{x}_u(n) = \textit{Innovations}$$




Flawed Case: Whiteness Test For the Flawed Case

Grace Clark



$$e_F(n) = x_F(n) - \hat{x}_u(n) = \text{Innovations}$$



The normalized auto-covariance $\hat{\rho}_e(i, k)$ of the innovations exceeds the statistical confidence interval bounds (blue)

⇒ Declare that the Innovations are “Not White”

⇒ There exists a model mismatch

⇒ *The unflawed model is **NOT** Valid for this cable*

⇒ ***An anomaly exists in the cable***


Flawed Case: WSSR Test For the Flawed Case

Grace Clark



$$\rho(l) = \sum_{k=l-N+1}^l \underline{e}^T(k) R_e^{-1}(k) \underline{e}(k) \quad \text{for } l \geq N \text{ (scalar)}$$

WSSR = Weighted Sum Squared Residuals



The WSSR exceeds the statistical bound (blue).

⇒ There exists a model mismatch

⇒ The unflawed model is **NOT** Valid for this cable

⇒ **An anomaly exists in the cable**

Discussion: The Model-Based Approach Offers Advantageous Properties

Grace Clark



- We can estimate the *LOCATION* of any detected anomaly.
- The algorithm is *robust* with respect to variations in the measured signals for various experimental scenarios:

==> If the TDR signals vary for various scenarios, we can model each case and test the cables effectively.
- This algorithm is very effective, even if we are given *only a single exemplar* of an unflawed cable signal.

Discussion: Future Work:

Grace Clark



- Thorough repeatability studies:
 - Measurement-to-measurement for one cable
 - Cable-to-cable
- Given an ensemble of measurements,
we can build more extensive performance measures:
 - Receiver Operating Characteristic (ROC) curves
Probability of Detection
vs. Probability of False Alarm
 - Statistical Confidence Interval about the estimated
probability of correct classification
- Experiments in a cable environment (not just bench-top)
- Cable “insult” studies using estimated damage types